

SAGA_CLOCK_COUNTER register



Overview

Clock-Cycle Counter register is a new SAGA Read-Only register. It is a unique feature, never seen in another existing 68k system. It allows to get, in real-time, the number of cycles consumed by one or more CPU instructions. This register can come in handy when a programmer needs to optimize their code and locate greedy routines.

Name

- SAGA_CLOCK_COUNTER

Address

- 0xDE0008

Access

- Read-Only

Size

- 32-bits
-

Description

Each time register is read, the internal counter is reinitialized to 0.

Can overflow if the delay between two calls is too long.

Example

TEST:

```
move.l #$CAFECAFE,d1 ; Operand for DIVU.L
tst.l $DE0008 ; Reset the Clock-Cycle counter
divu.l #100,d1 ; Consume some CPU cycles
move.l $DE0008,d0 ; D0 = Number of cycles consumed by the DIVU
instruction.
rts
```

Macros

```
DEBUG EQU 1

SAGA_CLOCK_COUNTER EQU $DE0008

CLKCNT_RESET MACRO
IFNE DEBUG
tst.l SAGA_CLOCK_COUNTER
ENDC
ENDM

CLKCNT_SAVE MACRO
IFNE DEBUG
move.l SAGA_CLOCK_COUNTER, __\1
ENDC
ENDM

CLKCNT_ADD MACRO
IFNE DEBUG
move.l d0, -(sp)
move.l SAGA_CLOCK_COUNTER, d0
add.l d0, __\1
move.l (sp)+, d0
ENDC
ENDM
```

MyRoutine:

```
move.l #$CAFECAFE,d1 ; Operand for DIVU
CLKCNT_RESET ; Reset the Clock-Cycle counter
divu.l #100,d1 ; Consume some CPU cycles
CLKCNT_SAVE MyCounter ; Save the number of cycles in MyCounter
RTS
```

MyCounter: DC.L 0

You are here: [start](#) » [saga](#) » [registers](#) » [saga_clock_counter](#)

From:

<http://wiki.apollo-accelerators.com/> - **Apollo Accelerators**

Permanent link:

http://wiki.apollo-accelerators.com/doku.php/saga:registers:saga_clock_counter

Last update: **2020/08/02 12:37**

